



- RADIAFLEX® functions as a distributed antenna to provide communications in tunnels, mines and large building complexes and is the solution for any application in confined areas.
- Slots in the copper outer conductor allow a controlled portion of the internal RF energy to be radiated into the surrounding environment. Conversely, a signal transmitted near the cable will couple into the slots and be carried along the cable length.
- RADIAFLEX® is used for both one-way and two-way communication systems and because of its broadband capability, a single radiating cable can handle multiple communication systems simultaneously.
- This RADIAFLEX® radiating cable utilize a low-loss cellular polyethylene foam dielectric and a corrugated copper outer conductor which offers a combination of remarkable flexibility, high strength and excellent electrical performance.

FEATURES / BENEFITS

- Broadband radiating cable supporting all wireless application between 30 MHz to 2750 MHz
- Ideally suited for application that require low bending radii
- Robust radiating cable operational under all enviromental conditions as e.g. harsh tunnels or mines



RCF cable, A-series

Technical features**GENERAL SPECIFICATIONS**

| | | |
|------|--|-------|
| Size | | 1-5/8 |
|------|--|-------|

ELECTRICAL SPECIFICATIONS

| | | |
|--|-----------------|---|
| Max. Operating Frequency | MHz | 2750 |
| Cable Type | | RCF |
| Impedance | Ohm | 50 +/- 2 |
| Velocity, percent | % | 89 |
| Capacitance | pF/m (pF/ft) | 75 (22.9) |
| Inductance, uH/m (uH/ft) | uH/m (uH/ft) | 0.188 (0.057) |
| DC-resistance inner conductor, ohm/km (ohm/1000ft) | Ω/km (Ω/1000ft) | 1.26 (0.38) |
| DC-resistance outer conductor, ohm/km (ohm/1000ft) | Ω/km (Ω/1000ft) | 0.55 (0.17) |
| Stop bands | MHz | None |
| Frequency Selection | MHz | 600, 900, 1800/1900, 2200, 2400, 2500, 2700 |

**MECHANICAL SPECIFICATIONS**

| | | |
|-------------------------------------|--------------|---|
| Jacket | | JFN |
| Jacket Color | | Standard Black, other colors on request |
| Jacket Description | | Halogen free, non corrosive, flame retardant, low smoke, polyolefin |
| Slot Design | | Milled (Two-Row) |
| Inner Conductor Material | | Corrugated Copper Tube |
| Outer Conductor Material | | Corrugated Copper Tube |
| Diameter Inner Conductor | mm (in) | 17.6 (0.69) |
| Diameter Outer Conductor | mm (in) | 46.5 (1.83) |
| Diameter over Jacket Nominal | mm (in) | 50.3 (1.98) |
| Minimum Bending Radius, Single Bend | mm (in) | 500 (19.7) |
| Cable Weight | kg/m (lb/ft) | 1.3 (0.87) |
| Tensile Force | N (lb) | 1080 (238) |
| Indication of Slot Alignment | | None |
| Recommended / Maximum Clamp Spacing | m (ft) | 1.2 (4) |
| Minimum Distance to Wall | mm (in) | 50 (1.97) |

TESTING AND ENVIRONMENTAL

| | | |
|------------------------|--|--|
| Jacket Testing Methods | | Test methods for fire behaviour of cable : IEC 60754-1/-2 smoke emission: halogen free, non corrosive IEC 61034 low smoke IEC 60332-1 flame retardant |
|------------------------|--|--|

TEMPERATURE SPECIFICATIONS

| | | |
|--------------------------|--------|-------------------------|
| Storage Temperature | °C(°F) | -70 to 85 (-94 to 185) |
| Installation Temperature | °C(°F) | -25 to 60 (-13 to 140) |
| Operation Temperature | °C(°F) | -40 to 85 (-40 to 185) |

**ATTENUATION**

| Frequency, MHz | Longitudinal Loss, dB/100 m (dB/100 ft) | Coupling Loss 50%, dB | Coupling Loss 95%, dB |
|----------------|---|-----------------------|-----------------------|
| 75 | 0.59 (0.18) | 62 | 74 |
| 150 | 0.86 (0.26) | 70 | 80 |
| 450 | 1.60 (0.49) | 83 | 93 |
| 800 | 2.25 (0.69) | 84 | 94 |
| 870 | 2.37 (0.72) | 82 | 92 |
| 900 | 2.42 (0.74) | 82 | 92 |
| 960 | 2.51 (0.77) | 82 | 92 |
| 1800 | 3.80 (1.16) | 81 | 91 |
| 1900 | 3.94 (1.20) | 80 | 90 |
| 2000 | 4.08 (1.24) | 80 | 90 |
| 2200 | 4.36 (1.33) | 80 | 90 |
| 2400 | 4.65 (1.42) | 80 | 90 |
| 2600 | 4.92 (1.50) | 80 | 90 |

[External Document Links](#)[Notes](#)

- Coupling loss as well as longitudinal attenuation of RADIAFLEX® cables are measured by the free space method according to IEC 61196-4.
- Coupling loss values are average values of all three spatial orientations (radial, parallel and orthogonal) of dipole antenna.
- Coupling loss values are given with a tolerance of +10 dB and longitudinal loss values with a tolerance of +5%. Note: Measured values below nominal are better. They are not limited by any tolerance-range.
- As with any radiating cable, the performance in building or tunnel environments may deviate from figures based on free space method.